

HP-A8 Owner's Manual V1.1 supplement

By updating the HP-A8 software to version 1.1, there are some changes in operation. This manual supplement describes the functions changed from the previous version and newly added functions. Please read this manual as well as the original owner's manual enclosed in the product.

Functions changed from the previous version

1. INPUT and VOLUME setting can now be memorized even after powering OFF.
2. Playing back DSD file can be chosen beyond folders within the SD card.
The maximum of 10 folders can be created in an SD card.
3. The DSD file name length is extended up to 53 characters including the extension name.
4. The number of files is increased from 20 to 30 per folder.
5. It now offers SYSTEM reset function. You can recall the factory default setting.
6. The USB processing is alleviated to ease the PC load for stable operation.
7. DTS signal to the digital input, such as Blu-ray multi-signal, used to generate noise.
This is now eliminated.
8. The headphone amp GAIN adjustable range is increased from 12dB to 20dB.

New Menu Parameter List

Name	Value	Default	Step
AMP GAIN	0dB to 20dB	0dB	0.5dB
UP Sampling	x1, x2, x4	x1	3
Digital Filter	SHARP ROLL OFF MAXIMUM DELAY	SHARP ROLL OFF	2
MSCK SEL	DIR, XTAL	DIR	2
DIRECT	OFF, ON	OFF	2
IN/VOL MEM	DISABLE INPUT VOLUME INPUT+VOLUME	DISABLE	4
SYSTEM INFO	Cur Ver Ver UP RESET	Cur Ver	3